MAINS CABLE BUNDLE RYANFIRE HP-X 1. ENSURE THE APERTURE IS CLEAN AND FREE OF ANY RYANROCK 6050 BUNDLE AND THE FLOOR, RECESSED BY 25MM FROM 125MM CONCRETE **FLOOR** BETWEEN THE CABLE BUNDLE AND THE FLOOR, TO A DEPTH OF 25MM, ON THE TOP SIDE OF THE FLOOR. 4. CLEAN ANY EXCESS SEALANT WITH A DAMP CLOTH.

RYANFIRE RYANROCK 6050 Products:

RYANFIRE HP-X

Approval: AS 1530.4:2014/4072.1:2005

BK: 226

Ref: 23SFR00047

ID: Ε

Scenario: Penetration seal to mains cable

bundle

Services: Up to Ø100mm cable bundle

> 7 x 25mm² mains 4 x 185mm² mains

Annular: 20 - 32mm

Construction: 125mm concrete floor

Fire Integrity: 120 minutes Fire Insulation: 45 minutes

Web based drawings are for example only, fire performance of any system is dependant on, but not limited to size of opening, substrate, if penetrations are passing through, type, size and number. Please refer to Ryanfire technical department for detailed and specific fire performance information.



RYANFIRE Technical Support: info@ryanfire.co.nz - Tel 09 443 0362

Ryanrock & HP-X to mains cable bundle 125mm concrete floor

Scale July 2025 NTS All errors and omissions excepted. The information contained within this drawing is believed to be correct on the date of publication, and is based upon tested and certified solutions. The policy of Ryanfire Products is one of constant improvement. Installers must ensure that they are following the latest published drawings, test evidence and instructions. Whilst Ryanfire Products will endeavour to keep its publications up to date, the accuracy of the information contained within this drawing may be affected by pertinent changes in the law or regulatory requirements and alterations or Drawing Number

V29.61

Ryanfire Products owns and has copyright to these drawings. They are to be used only for the purpose for which they were intended and supplied and are not to be sold, transferred or made available for use by a third party. Any misuse of these drawings will result in legal proceedings.

INSTALLATION INSTRUCTIONS

INSERT 100MM THICK LAYER OF RYANROCK 6050 INTO THE ANNULAR GAP BETWEEN THE CABLE

APPLY RYANFIRE HP-X INTO THE ANNULAR GAP

amendments to the specification of the manufactured products. Terms and conditions of sale apply.

DUST AND DEBRIS.

THE TOP.

1.0